

Compatibility List of Battery for Solinteg Hybrid Inverter

Ver.1.10 , Jun. 12, 2024 updated

Solinteg MHS-3-8K series high voltage hybrid inverter

Battery Brand	Battery Pattern	Comm.	Battery ID in the Inverter	Inverter Version	RJ45 PIN used
Solinteg	EBS-B2K5	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL
Pylontech	Force H1/H2(-V2) Powercube X1/X2/H1/H2(-V2)	CAN	Pylon_HV	V1.00. xx. xx. xx V1.18. xx. xx. xx	4 - CANH 5 - CANL
Dyness	Tower/Tower Pro PowerRack (HV1/HV2/HV4)	CAN	Dyness	V1.01. xx. xx. xx V1.15. xx. xx. xx	4 - CANH 5 - CANL
Wattsonic	2.3kWh (3-8)	CAN	Wattli_HV	V1.00. xx. xx. xx V1.18. xx. xx. xx	4 - CANH 5 - CANL
Soluna	Soluna 10K HV, Soluna 15K HV	CAN	Soluna_HV	V1.01. xx. xx. xx V1.02. xx. xx. xx	4 - CANH 5 - CANL
Weco	5K3XP (High Voltage)	CAN	Weco_HV	V1.01. xx. xx. xx V1.02. xx. xx. xx	1 - CANH 2 - CANL
Ipotisedge	Mint-JKE05, Mint-JKE10, Mint-JKE15	CAN	Mint-JKE	V1.01. xx. xx. xx V1.08. xx. xx. xx	Adapter to for port connection
FEB	HV5120-S1	CAN	Default HV_1	V1.01. xx. xx. xx V1.10. xx. xx. xx	4 - CANH 5 - CANL
STELTEC	Focus-H1(STE-BC50/STE-BSH-2560)	CAN	Default HV_1	V1.01. xx. xx. xx V1.10. xx. xx. xx	4 - CANH 5 - CANL
Lithium Valley	LV-BST-H2.56, LV-BST-H5.12	CAN	Default HV_1	V1.01. xx. xx. xx V1.15. xx. xx. xx	4 - CANH 5 - CANL
Sunwoda	SunESS-H	CAN	Sunwoda_HV	V1.01. xx. xx. xx V1.16. xx. xx. xx	4 - CANH 5 - CANL 7 - Wakeup+(5VDC) 8 - Wakeup-
Yoshopo	NOVA 3000, NOVA 5000	CAN	Default HV_1	V1.01. xx. xx. xx V1.08. xx. xx. xx	4 - CANH 5 - CANL
Pytes	HV4850, HV48100	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL
BSLBATT	Matchbox HVS Series	CAN	Default HV_1	V1.01. xx. xx. xx V1.22. xx. xx. xx	4 - CANH 5 - CANL
DMEGC	H01	CAN	Default HV_1	V1.01. xx. xx. xx V1.23. xx. xx. xx	4 - CANH 5 - CANL
Raystech	RT5427HV	CAN	Default HV_1	V1.01. xx. xx. xx V1.27. xx. xx. xx	4 - CANH 5 - CANL
BETTENERGY	ELEBOX-2560, ELEBOX-5K-HV	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL

Solinteg MHT-4-20K series high voltage hybrid inverter

Battery Brand	Battery Pattern	Comm.	Battery ID in the Inverter	Inverter Version	RJ45 PIN used
Solinteg	EBS-B2K5 EBR-B5K3	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL
Pylontech	Force H1/H2(-V2) Powercube X1/X2/H1/H2(-V2)	CAN	Pylon_HV	V1.00. xx. xx. xx V1.18. xx. xx. xx	4 - CANH 5 - CANL
Dyness	Tower/Tower Pro PowerRack (HV1/HV2/HV4/HV4F) PowerStone	CAN	Dyness	V1.01. xx. xx. xx V1.15. xx. xx. xx	4 - CANH 5 - CANL
Wattsonic	2.3kWh (3-5) 3.84kWh (3-5)	CAN	Wattli_HV	V1.00. xx. xx. xx V1.18. xx. xx. xx	4 - CANH 5 - CANL
Soluna	Soluna 10K HV, Soluna 15K HV	CAN	Soluna_HV	V1.01. xx. xx. xx V1.02. xx. xx. xx	4 - CANH 5 - CANL
Weco	5K3XP (High Voltage)	CAN	Weco_HV	V1.01. xx. xx. xx V1.02. xx. xx. xx	1 - CANH 2 - CANL
Ipotisedge	Mint-JKE10, Mint-JKE15, Mint-JKE20	CAN	Mint-JKE	V1.01. xx. xx. xx V1.08. xx. xx. xx	Adapter to for port connection
FEB	HV5120-S1	CAN	Default HV_1	V1.01. xx. xx. xx V1.10. xx. xx. xx	4 - CANH 5 - CANL
STELTEC	Focus-H1(STE-BC50/STE-BSH-2560)	CAN	Default HV_1	V1.01. xx. xx. xx V1.10. xx. xx. xx	4 - CANH 5 - CANL
Lithium Valley	LV-BST-H2.56, LV-BST-H5.12	CAN	Default HV_1	V1.01. xx. xx. xx V1.15. xx. xx. xx	4 - CANH 5 - CANL
Sunwoda	SunESS-H	CAN	Sunwoda_HV	V1.01. xx. xx. xx V1.16. xx. xx. xx	4 - CANH 5 - CANL 7 - Wakeup+(5VDC) 8 - Wakeup-
	CISS 50~70 Series CISS 25~70-R Series	CAN	Default HV_1	V1.01. xx. xx. xx V1.16. xx. xx. xx	4 - CANH 5 - CANL
Yoshopo	NOVA 3000, NOVA 5000	CAN	Default HV_1	V1.01. xx. xx. xx V1.08. xx. xx. xx	4 - CANH 5 - CANL
Pytes	HV4850, HV48100	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL
BSLBATT	Matchbox HVS Series	CAN	Default HV_1	V1.01. xx. xx. xx V1.22. xx. xx. xx	4 - CANH 5 - CANL
DMEGC	H01	CAN	Default HV_1	V1.01. xx. xx. xx V1.23. xx. xx. xx	4 - CANH 5 - CANL
Raystech	RT5427HV	CAN	Default HV_1	V1.01. xx. xx. xx V1.27. xx. xx. xx	4 - CANH 5 - CANL
BETTENERGY	ELEBOX-2560, ELEBOX-5K-HV	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL

Solinteg MHT-25-50K series high voltage hybrid inverter

Battery Brand	Battery Pattern	Comm.	Battery ID in the Inverter	Inverter Version	RJ45 PIN used
Solinteg	EBS-B2K5 EBR-B5K3	CAN	Default HV_1	V1.01. xx. xx. xx V1.26. xx. xx. xx	4 - CANH 5 - CANL
Pylontech	Force H1/H2(-V2) Powercube X1/X2/H1/H2(-V2) Powercube M1/M2/M3	CAN	Pylon_HV	V1.01. xx. xx. xx V1.08. xx. xx. xx	4 - CANH 5 - CANL
Dyness	Tower/Tower Pro PowerRack (HV1/HV2/HV4/HV4F) PowerStone	CAN	Dyness	V1.01. xx. xx. xx V1.15. xx. xx. xx	4 - CANH 5 - CANL
Wattsonic	3.84kWh Commercial (6-17/Rack)	CAN	Wattli_HV	V1.01. xx. xx. xx V1.08. xx. xx. xx	4 - CANH 5 - CANL
Weco	5K3XP (High Voltage) 14K3XP (High Voltage)	CAN	Weco_HV	V1.01. xx. xx. xx V1.08. xx. xx. xx	1 - CANH 2 - CANL
Lithium Valley	LV-BST-H2.56, LV-BST-H5.12, LV- IESS	CAN	Default HV_1	V1.01. xx. xx. xx V1.15. xx. xx. xx	4 - CANH 5 - CANL
Sunwoda	CISS 50~70 Series CISS 25~70-R Series	CAN	Default HV_1	V1.01. xx. xx. xx V1.16. xx. xx. xx	4 - CANH 5 - CANL

Note: The list will be updated periodically. For any query, please contact service@solinteg.com